

Golden Island Nevada

➔ Better games through innovation!



www.tab.at



Service Manual

TAB-Austria Industrie- und Unterhaltungselektronik GmbH & CoKG

Haider Strasse 40, A-4052 Ansfelden

Tel.+43 (0)7229/78 040-0*, Fax +43 (0)7229/78 660, e-mail: sales@tab.at

Hotline: +43 (0)7229/78 040-250, e-mail: hotline@tab.at



Thank you for choosing

Golden Island

in preference to the vast number of other Slot-machines available on the market.

To gain satisfactory use from your Golden Island, please read the operating instructions thoroughly.

Please store this manual in such a way to have it ready at hand when required.

For additional queries, our Hotline is at your service.

Call +43-7229-780 40 – ext. 250

Operating instructions **Golden Island** Machines manual. (English)

Valid for Versions: GI - V1.12 S322 or higher

(CG/HJP/EK – January 8, 2008)

The text passages and illustrations contained within this document were put together with the greatest amount of care and attention, however, mistakes cannot be completely ruled out.

The manufacturer accepts no legal responsibility or liability in any form with regard to errors in detail and any consequences that may arise from such errors.

The manufacturer is thankful for any suggestions for improvement or pointers leading to errors.

All rights – including any arising from photomechanical reproduction and storage in electronic or any other medium – are reserved. The program, handbook and all components are subject to international copyright regulations.

© 1996-2008

TAB - Austria

A-4052 Ansfelden, Haider-Straße 40

Tel. +43-7229-780 40 - 0*, Fax +43-7229-78 660

All rights reserved.



Index

<u>SETUP POINTERS</u>	7
<u>INITIAL OPERATION</u>	8
<u>SHORT INSTRUCTIONS</u>	9
PROGRAM UPDATE	9
UPDATE AT MACHINE	9
ERROR HANDLING WITH DEFECT HARDWARE	11
1) INTEGRITY CHECK AT STARTUP FAILED	11
2) HARDWARE ERROR OF HDD	11
3) HARDWARE ERROR OF FRAM	11
<u>DESCRIPTION OF THE MACHINE</u>	12
GENERAL	12
OPERATING ELEMENTS	12
<u>PC SYSTEM COMPONENTS</u>	13
STANDARD	13
OPTIONAL	13
<u>TECHNICAL DATA</u>	14
MACHINE SIZES	14
ELECTRIC DATA	14
<u>SERVICE FUNCTIONS - SUPERVISORS</u>	15
ACTIVATION OPTIONS	15
<u>MAIN PAGE WITH IDENTIFICATION FOR HEAD SUPERVISOR</u>	16
<u>MAIN PAGE WITH IDENTIFICATION (SUPERVISOR1 – 3)</u>	17
1) HEAD SUPERVISOR - MAIN PAGE	18
1.1) HEAD SUPERVISOR → OWN BOOKKEEPING	19
1.2) HEAD SUPERVISOR → SUPERVISOR ACCOUNTS (1 - 3)	20
1.3) HEAD SUPERVISOR → LAST 5 BILL AND GAME DATA	21
1.4) HEAD SUPERVISOR → ACCOUNTING → MAIN ACCOUNTING	22
1.5) HEAD SUPERVISOR → ACCOUNTING → ACCOUNTING	23



1.6) HEAD SUPERVISOR → ACCOUNTING → PROTOCOL	24
1.7) HEAD SUPERVISOR → PIN SETTINGS	25
1.8) HOPPER REFILL	26
1.9) HEAD SUPERVISOR → BASIC SETTINGS	27
2) SUPERVISOR (1 - 3) MAIN PAGE	28
2.1) SUPERVISOR → LAST 5 BILL AND GAME DATA	29
2.2) SUPERVISOR (1 - 3) → ACCOUNTING	30
2.3) SUPERVISOR (1 - 3) → PIN SETTINGS	31
2.4) SUPERVISOR (1 - 3) → REFILL HOPPER	32
2.5) SUPERVISOR (1 - 3) → BASIC SETTINGS	33
1) GAME DESCRIPTIONS	34
<hr/>	
1.1) GAME SELECTION	34
1.1) DESCRIPTION	34
2) KENO	35
2.1) GAME DESCRIPTION	35
2.2) GAME SEQUENCE	35
2.3) WINNING COMBINATIONS AND THE CORRESPONDING WIN FACTORS	36
3) ROYAL LINER	38
3.1) GAME DESCRIPTION	38
3.2) GAME SEQUENCE	38
3.3) WINNING COMBINATIONS AND THE CORRESPONDING WIN FACTORS	39
4) CARIBBEAN GOLD	42
4.1) GAME DESCRIPTION	42
4.2) GAME SEQUENCE	42
4.3) WINNING COMBINATIONS AND THE CORRESPONDING WIN FACTORS	43
5) ROULETTE	46
5.1) GAME DESCRIPTION	46
5.2) GAME SEQUENCE	46
5.3) WINNING COMBINATIONS AND THE CORRESPONDING WIN FACTORS	48
6) ROYAL POKER	50
6.1) GAME DESCRIPTION	50
6.2) GAME SEQUENCE	50
6.3) DESCRIPTION „ACES-BONUS“	51
6.4) WINNING COMBINATIONS AND THE CORRESPONDING WIN FACTORS	52
7) GAMBLE-LADDER	54
7.1) DESCRIPTION	54
TROUBLESHOOTING	55
<hr/>	
CABLE PLAN	58
<hr/>	
DECLARATION OF CE CONFORMITY	59
<hr/>	
END-USER LICENSE AGREEMENT FOR MICROSOFT SOFTWARE	60
<hr/>	





WARRANTY TERMS BY TAB-AUSTRIA INDUSTRIE UND UNTERHALTUNGSELEKTRONIK GESELLSCHAFT M.B.H. & CO KG	63
--	-----------

NOTES	66
--------------	-----------



Setup Pointers

Safety regulations for the user:

- The machine may only be operated in dry rooms and connected to a safety plug socket that complies with the relevant safety standards.
- Before starting the machine, it should be allowed to attain room temperature.
- Check the main voltage before connecting the machine!
- The machine is designed for 230 VAC (or 115 Volt if specified on the type plate), 50 Hz (or 60 Hz) and 180 W.
- The machine may only be operated with a 3.15 amp fuse.
- In case of breakage to housing parts, protruding wires, machine fires or smashed picture tubes the machine must be immediately switched off and the main plug disconnected.
- Defective or bare electric wires or cables, especially power cables and plug connectors must be replaced.
- The recommended ambient temperature is 5 – 35 Degrees on the Celsius scale.
- The recommended working temperature is 15 – 40 Degrees on the Celsius scale.
- The recommended absolute humidity is between 30% and 75% RG, not condensed.

IMPORTANT!

In such cases ensure that any machine contact is avoided and that it cannot be switched on!

- When positioned alongside other machines, interference in normal operation may occur.

Please pay attention to the [licensing terms and conditions of Microsoft](#).



**Disposal of Old Electrical & Electronic Equipment
(Applicable in the European Union and other European
countries with separate collection systems)**

This symbol on the product or on its packaging indicates that this product shall not be treated as household waste. Instead it shall be handed over to the applicable collection point for the recycling of electrical and electronic equipment. By ensuring this product is disposed of correctly, you will help prevent potential negative consequences for the environment and human health, which could otherwise be caused by inappropriate waste handling of this product. The recycling of materials will help to conserve natural resources. For more detailed information about recycling of this product, please contact your local city office, your household waste disposal service or the company where you purchased the product.




Initial Operation

Each machine has already been tested at the factory and is delivered with initial settings pre-programmed.

We recommend a 15 minutes warm up time before initial operation so that the machine can reach optimal operation temperature.

However, temperature differences can change the touch screen settings so that they are no longer correct. Therefore, when a machine is put in operation for the first time, we recommend to **ALWAYS** observing the following procedure:

1. **Turn on the machine:**
With the switch located on the back, the program starts automatically.
2. **Open the front door and turn on the operator switch:**
The Golden Island operator mode appears on the screen.
3. **Calibration of the touch screen:**
Tap "Basic settings", then "Calibration".
Sit in a perfectly straight way, well-centered position, at a 90° angle in front of the machine and follow the instructions on the display exactly.
4. **Setting the volume:**
Under "Basic settings" you can adjust the volume for the game mode and the stand-by mode by using the  buttons.
5. Via the "**Back**" button you reach the test mode main menu, turn off the operator switch and the game area is automatically restarted.



Short Instructions

Program Update

Every machine is delivered pre-programmed, when changing to a new version an update must be carried out.

Update at Machine

The “Golden Island” software is on the installed HDD in the PC of the machine. To update the content of installed HDD you must first plug the update HDD to the external connector. In some configurations the plug connector is plumbed and an update can only be made by opening the plumb and connect the update disk via an IDE cable within the PC box. After power on the update process starts automatically.

Important:

During an update the PC must be an integral part of the machine.

Furthermore the machine (*e.g. VC2, Strato-Steel, Cosmo or Nevada*) must be connected to the correct cable harness. The update program detects and checks the cable harness automatically which ensures that correct software is installed.

Starting from version 1.13 a writing protection (EWF) is installed on the hard disk. This means no data can be saved on the hard disk.

However the touch screen calibration writes the first time certain initial data on the hard disk.

→ **Because of that the touch screen calibration must be absolutely accomplished during the update. Immediately after the update the writing protection is active. Afterwards at any time only the 2-point-calibration of the touch screen can be accomplished.**

However if during the update the first touch screen calibration is not accomplished, these initials data are not written - and the touch screen won't work correctly until new update with touch screen calibration is done.

Procedure:

- Switch machine off.
- Dock the update HDD to the plug connector of the PC.
- Switch machine on.
- If the update tool finds an activated operator switch, you may choose for additional update options.
- Copy procedure is started automatically.
- The internal hard disk is checked and if necessary newly setup.
A restart of the machine may be forced.



- Turn machine off at final message *“Update finished – Please switch off, remove update disk and switch on again“*.
- Test function is started automatically (*duration approximately. 1-2 min., procedure is the same as copying*).
- Wait for final message *“Initialization complete – Please press Restart to finish”* or wait 30 seconds for automatic restart of the machine.
- After initial setup a touch screen calibration is started automatically.
- Calibrate touch screen or wait 30 seconds for automatic finish without new calibration.
- Update process is finished when game software is started.



Error handling with defect hardware

1) Integrity check at startup failed

The machine stops with an error message on the screen: “**Program Error (hard disc)**”; no more credits will be accepted; no more action from the player is possible; operator invention is required.

Solution:

An update has to be performed with an update disk with the same version by an authorized person.

After that the “Critical Memory” will be restored from the data’s in the FRAM (*if they are correct*) to the hard disk. If there is still an error, the hard disk is defect and must be changed.

2) Hardware error of HDD

In this case, mostly the machine will not work anyway.

Solution:

Hard disk has to be changed by an authorized person only. The new hard disk has to contain the same version or an update has to be performed on the machine with an update disk containing the same version.

After that the “Critical Memory” will be restored from the data’s in the FRAM (*if they are correct*) to the new internal hard disk.

3) Hardware error of FRAM

A “blue screen” will be shown and the machine stops immediately.

Solution:

I/O Controller card has to be changed by an authorized person only.

After that the “Critical Memory” will be restored from the data’s on the hard disk (*if they are correct*) to the FRAM on the new I/O Controller card.



Description of the Machine

General


“Golden Island” is an ergonomically designed slot machine. The machine contains an electronic coin acceptor, a 19" TFT-Display with touch screen, a second 19" TFT-Display(info panel) and a complete PC system. Optionally - depending on the model - up two hoppers and a banknote reader can be added to the machine.

Operating Elements

All games in the “Golden Island” are played via touch screen and/or push buttons. There are totally 6 push buttons that can be used optionally to the touch screen for various functions.

The functions of the operator mode are precisely described in the operators manual.

By switching on operator mode at booting the machine you are able to enter the following programs (only during normal start):



Request File check:

⇒ Manual data integrity test will be performed.

Request touch calibration:

⇒ Calibration of the touch screen will be performed.



PC System Components

Standard

- PC-System with Intel Pentium 4 Processor (2,4 GHz), PCI-Bus and min. 256 MB RAM
- On-Board display adapter with ATI chipset, (1280 x 1024 Pixel resolution, High Color)
- On-Board 16 bit sound card
- Min. 20 GB hard disk
- TAB I/O Interface card with security memory
- Two 19" TFT displays
- USB Touch-Screen Controller
- Electronic coin acceptor

Optional

- Banknote reader (*ASTRO Systems HR1*)
- Switch lock system (*EKEY-Rupp or EKEY-TAB*)
- Remote key switch
- One or two Hopper (*Azkoyen Rode U II plus*)



Technical data

Machine sizes

	unpacked	packed
Depth	54 cm	59 cm
Width	52 cm	77 cm
Height	175 cm	182 cm
Weight	112 kg ¹	123 kg

Electric data

Power connection: 230 VAC 50-60Hz to plug socket

Power: 180 watts

Fuse: 3.15 ampere

Note:

The following should be observed when connecting several machines to a power distributor:

No more than three machines should be connected to one properly installed power connection, which should possess a 13-amp fuse.

¹ The weight may vary depending on the installed optional components.



Service functions - supervisors

Service functions are activated with the service switch. The functions can be called up from menu control and before every game start.

Note:

Several accounting functions can be limited or deactivated or can be unavailable depending your machine's configuration.

Different services can be called up depending on the authorization status. The head supervisor has the highest authorization status and can therefore administrate the PIN of the three other supervisors. In addition, the accounts of the different supervisors are administrated. These accounts merely serve as accounts between the head supervisor and the other supervisors and play no role in the main bookkeeping.

If the head supervisor has no PIN it is not possible to activate supervisors 1-3, as an authentication (switch) and identification (PIN) is necessary for distinction. Without a PIN only the head supervisor has a supervising function.

The volume can be adjusted independent of the supervisor for the game and standby mode.

Term Descriptions:

- Operator: Owner of the machine.
The Operator has the highest authorization in the operator mode.
- Head Supervisor: Operator or administrator of the machine.
The Head supervisor has the second highest authorization status and accounts the cashbox content with the operator.
- Supervisor(s): Supervisors have only attending functions.
Accounting is only possible with the head supervisor.
- Hardlock-Dongle: Defines the configuration of the game software.
All requirements of the country-specific license are adjusted here.

Activation Options

When activating the operator switch and simultaneously pressing specific pushbuttons the following functions can be called up:

- Left green pushbutton: Touch screen calibration
- Left yellow pushbutton: Touch screen test
- Left red pushbutton: Monitor test picture



Main Page with identification for Head supervisor

After entering the PIN wrong three times the PIN is locked for one hour. If PIN is locked, it can be unlocked by an authorized person only (*operator*).

Service

GI/INT - 1(V1.12 - System 322A)

Fri. , July 14, 2006, 10:28 o'clock

Head supervisor - Enter four-digit PIN!

1	2	3
4	5	6
7	8	9
0	Cancel	



Main Page with identification (Supervisor1 – 3)

By pressing the appropriate push button the supervisor must authenticate and then identify by inserting the PIN. After entering the PIN wrong three times the PIN is locked for one hour. If PIN is locked it be unlocked by a person with a higher authorization status only (e.g. *head supervisor*).

Service

GI/INT - 1(V1.12 - System 322A)

Fri., July 14, 2006, 10:24 o'clock

Head supervisor	Supervisor 1
Supervisor 2	Supervisor 3



1) Head Supervisor - Main Page

Here electronic bookings can be carried out.

The section "Push up" is only available, if it is enabled in the operator mode.

The section "Push down" is only available, if it is enabled in the operator mode.

Service

Head supervisor

Supervisory accounting

Own

Supervisor 1

Supervisor 2

Supervisor 3

Last 5 bill and game data

Accounting

Pin settings

Refill hopper

Basic settings

Push up

0 Credit
(0,00 EUR)

100

200

500

1000

Push down

0 Credit
(0,00 EUR)

Push down



1.1) Head Supervisor → Own Bookkeeping

This page displays the own bookings. The deletion of this account is possible at any time and does not affect the main bookkeeping.

By pressing the “Delete” button, the bookkeeping is deleted.

Service

GMINT - 1(V1.12 - System 322A)

Accounting - Supervisor 1 - Supervisor 3

	Push up	Push down	Hopper 1 refill
Supervisor 1	0,00 EUR	0,00 EUR	0,00 EUR
Supervisor 2	0,00 EUR	0,00 EUR	0,00 EUR
Supervisor 3	0,00 EUR	0,00 EUR	0,00 EUR

Accounting - Head supervisor

Thurs., July 13, 2006, 17:30 o'clock - Fri., July 14, 2006, 9:09 o'clock

Push up	0,00 EUR	(+)
Remote	0,00 EUR	(+)
Push down	0,00 EUR	(-)
Hopper 1 refill	0,00 EUR	(-)
Hopper 2 refill	0,00 EUR	(-)
<hr/>		
Total difference	0,00 EUR	+

Delete

Back



1.2) Head Supervisor → Supervisor Accounts (1 - 3)

The head supervisor has access to the accounts of up to three supervisors. The supervising accounts can be deleted (balanced) here.

Service

GI/INT - 1(V1.12 - System 322A)

Statement Supervisor 1 _____

Thurs., July 13, 2006, 17:30 o'clock - Fri., July 14, 2006, 9:28 o'clock

Push up	0,00 EUR (+)
Push down	0,00 EUR (-)
Hopper 1 refill	0,00 EUR (-)
Hopper 2 refill	0,00 EUR (-)
<hr/>	
Total	0,00 EUR +
<hr/>	

Supervisor 1 - Please insert the servicekey to delete the bookkeeping!

Delete

Back



1.3) Head Supervisor → Last 5 bill and game data

The head supervisor can review a history list of the last five played games and the last five accepted banknotes with date and timestamp.

Service

GMINT - 1 (V1.12 - System 322A)

Last 5 bill and game data

Last 5 game data

Date	Time	Game	Bet	Winner P...	Collected	TOTIN	TOTOUT

Last 5 bill data

Date	Time	Bank note



1.4) Head Supervisor → Accounting → Main accounting

The head supervisor has access to the main accounting of the operator.
Account can't be changed or deleted.

Service

GMINT - 1 (V1.12 - System 322A)

Main accounting

Accounting

Protocol

Main accounting

Wed., July 26, 2006, 16:44 o'clock - Thurs., July 27, 2006, 8:21 o'clock

Remote	0,00 EUR +	Remote	0,00 EUR +
Push up	0,00 EUR +	Push up	0,00 EUR +
Bank note	0,00 EUR +		
Coin	0,00 EUR +		
<hr/>		<hr/>	
Total IN	0,00 EUR	External IN	0,00 EUR
<hr/>		<hr/>	
Push down	0,00 EUR +	Push down	0,00 EUR +
Hopper OUT	0,00 EUR +	Hopper Refill	0,00 EUR +
<hr/>		<hr/>	
Total OUT	0,00 EUR	External OUT	0,00 EUR
<hr/>		<hr/>	
Total difference	0,00 EUR +	External difference	0,00 EUR +
<hr/>		<hr/>	
Power On	0	Cashboxdoor	0
		Frontdoor	0

Back



1.5) Head Supervisor → Accounting → Accounting

The head supervisor has access to his account for the actual accounting period. The deletion of this account is possible at any time and does not affect the main bookkeeping (operator account).

Service

GMINT - 1(V1.12 - System 322A)

Main accounting

Accounting

Protocol

Accounting

Wed., July 26, 2006, 16:44 o'clock - Thurs., July 27, 2006, 8:21 o'clock

Remote	0,00 EUR +	Remote	0,00 EUR +
Push up	0,00 EUR +	Push up	0,00 EUR +
Bank note	0,00 EUR +		
Coin	0,00 EUR +		
<hr/>		<hr/>	
Total IN	0,00 EUR	External IN	0,00 EUR
<hr/>		<hr/>	
Push down	0,00 EUR +	Push down	0,00 EUR +
Hopper OUT	0,00 EUR +	Hopper Refill	0,00 EUR +
<hr/>		<hr/>	
Total OUT	0,00 EUR	External OUT	0,00 EUR
<hr/>		<hr/>	
Total difference	0,00 EUR +	External difference	0,00 EUR +
<hr/>		<hr/>	

Delete

Back



1.6) Head Supervisor → Accounting → Protocol

Here the supervisor can see all pushup, pushdown and remote booking actions in currency values by date and time.

Service

GI/INT - 1(V1.12 - System 322A)

Main accounting Accounting Protocol

07/17/06 11:22:16	Head supervisor	Remote	1,00 EUR
07/19/06 11:00:21	Head supervisor	Remote	1,00 EUR

Zurück



1.7) Head Supervisor → Pin settings

The head supervisor can change PIN settings for himself and for the other supervisors. If a lock icon appears, it means that the supervisor's PIN has been disabled after three false PIN entries. After selecting the specific supervisor it can be unlocked.

Service

GI/INT - 1 (V1.12 - System 322A)

Change PIN - activate user

Please select the supervisor whose PIN is to be changed.

<input type="radio"/> Head supervisor <input checked="" type="checkbox"/> Activated	<table border="1" style="width: 100%; border-collapse: collapse;"><tbody><tr><td style="width: 33%; height: 40px; text-align: center;">1</td><td style="width: 33%; height: 40px; text-align: center;">2</td><td style="width: 33%; height: 40px; text-align: center;">3</td></tr><tr><td style="height: 40px; text-align: center;">4</td><td style="height: 40px; text-align: center;">5</td><td style="height: 40px; text-align: center;">6</td></tr><tr><td style="height: 40px; text-align: center;">7</td><td style="height: 40px; text-align: center;">8</td><td style="height: 40px; text-align: center;">9</td></tr><tr><td style="height: 40px; text-align: center;">0</td><td colspan="2" style="height: 40px; text-align: center;">Cancel</td></tr></tbody></table>	1	2	3	4	5	6	7	8	9	0	Cancel	
1		2	3										
4		5	6										
7		8	9										
0	Cancel												
<input type="radio"/> Supervisor 1 <input checked="" type="checkbox"/> Activated													
<input type="radio"/> Supervisor 2 <input type="checkbox"/> Activated													
<input type="radio"/> Supervisor 3 <input type="checkbox"/> Activated													



1.8) Hopper Refill

The hopper can only be refilled by inserting coins into the coin acceptor.

Service

GM/NT - 1(V1.12 - System 322A)

Refill hopper - Hopper 1

Hopper content	0 Coins	0,00 EUR
Current refill	0 Coins	0,00 EUR

Insert coins to refill.(2,00 EUR)

Refill hopper - Hopper 2

Hopper content	0 Coins	0,00 EUR
Current refill	0 Coins	0,00 EUR


Insert coins to refill.(1,00 EUR)



1.9) Head Supervisor → Basic settings

On this page the following basic settings can be done:

- Calibration of the touch screen
- Test the calibration of the touch screen
- Volume setting (Game)
- Volume setting (Standby)



The screenshot displays the 'Service' menu for 'GI/INT - 1 (V1.12 - System 322A)'. It features two main buttons at the top: 'Calibration' and 'Test calibration'. Below these is a 'Volume' section containing two sliders. The 'Game' slider is set to 6, and the 'Standby' slider is set to 5. Each slider has a blue bar indicating the current level and a set of control buttons: a left arrow, a right arrow, 'MIN', and 'MAX'. At the bottom of the menu are two buttons: 'Standard' and 'Back'.



2) Supervisor (1 - 3) Main Page

Electronic bookings can be carried out here.

The section "Push up" is only available, if it is enabled in the operator mode.

The section "Push down" is only available, if it is enabled in the operator mode.

Service

GI/INT - 1(V1.12 - System 322A)

Supervisor 1

Credit information

Credit	0
--------	---

Last 5 bill and game data

Accounting

Pin settings

Refill hopper

Basic settings

Push up

0 Credit	
(0,00 EUR)	
100	200
500	1000

Push down

0 Credit	
(0,00 EUR)	
Push down	

Back



2.1) Supervisor → Last 5 bill and game data

Here the supervisor can see a history list with the last five played games and the last five accepted banknotes with date and timestamp.

Service

GMINT - 1(V1.12 - System 322A)

Last 5 bill and game data

Last 5 game data

Date	Time	Game	Bet	Winner P...	Collected	TOTIN	TOTOUT

Last 5 bill data

Date	Time	Bank note



2.2) Supervisor (1 - 3) → Accounting

Displays refilled coins, Push up and Push down actions.

Service

GMINT - 1(V1.12 - System 322A)

Statement Supervisor 1

Wed., July 26, 2006, 16:44 o'clock - Thurs., July 27, 2006, 8:20 o'clock

Push up	0,00 EUR (+)
Push down	0,00 EUR (-)
Hopper 1 refill	0,00 EUR (-)
Hopper 2 refill	0,00 EUR (-)
<hr/>	
Total	0,00 EUR +
<hr/>	



2.3) Supervisor (1 - 3) → Pin settings

Here the supervisor can assign a new PIN.

Service

GI/INT - 1(V1.12 - System 322A)

Change PIN - activate user (Supervisor 1)

Please enter a new 4-digit PIN to change your PIN.

????

1	2	3
4	5	6
7	8	9
0	Cancel	



2.4) Supervisor (1 - 3) → Refill Hopper

The hopper can only be refilled by inserting coins into the coin acceptor.

The coins are routed to the correct hopper automatically, e.g. coin 2€ → Hopper1, coin 1€ → Hopper2.

Service

GMINT - 1(V1.12 - System 322A)

Refill hopper - Hopper 1

Hopper content	0 Coins	0,00 EUR
Current refill	0 Coins	0,00 EUR

Insert coins to refill.(2,00 EUR)

Refill hopper - Hopper 2

Hopper content	0 Coins	0,00 EUR
Current refill	0 Coins	0,00 EUR


Insert coins to refill.(1,00 EUR)



2.5) Supervisor (1 - 3) → Basic settings

On this page the following basis settings can be done:

- Calibration of the touch screen
- Test the calibration of the touch screen
- Volume setting (Game and/or Standby)



Service
GI/INT - 1(V1.12 - System 322A)

Calibration Test calibration

Volume

Game 6

Standby 5

Standard Back



1) Game descriptions

1.1) Game Selection

The number of available games and type of game be ruled by actual configuration



Screenshot 1

1.1) Description

The player can start a game, choose a language or payout his credit-account.



2) Keno



Screenshot 2

2.1) Game description

Guess up to ten numbers out of twenty random given numbers.

2.2) Game sequence

1. Select up to ten numbers by touch screen or "select 10" – button
2. The game is started with the "Start" button.
3. The computer calculates and displays twenty random numbers.
4. Keno winnings calculation




2.3) Winning combinations and the corresponding win factors

Please note that win factors may be limited by actual configuration!

Selected Numbers	Winning Numbers	Win Factor
		x 1000
		x 800
		x 250
		x 80
		x 12
		x 5
		x 3

Selected Numbers	Winning Numbers	Win Factor
		x 900
		x 750
		x 200
		x 52
		x 10
		x 2

Selected Numbers	Winning Numbers	Win Factor
		x 800
		x 450
		x 110
		x 10
		x 3
		x 1



Keno – winnings (continue)

Selected Numbers	Winning Numbers	Win Factor
		x 700
		x 120
		x 15
		x 8
		x 2

Selected Numbers	Winning Numbers	Win Factor
		x 600
		x 80
		x 15
		x 2

Selected Numbers	Winning Numbers	Win Factor
		x 250
		x 37
		x 5


Selected Numbers	Winning Numbers	Win Factor
		x 87
		x 7
		x 2

Selected Numbers	Winning Numbers	Win Factor
		x 35
		x 4

Selected Numbers	Winning Numbers	Win Factor
		x 16



3) Royal Liner



Screenshot 3

3.1) Game description

Bet on up to five win lines with three symbols.
 Nine reels spin by pressing the 'Start button' and will stop automatically.
 The winnings for the maximum of 5 winning lines will be added.
 All wins pay from left to right

3.2) Game sequence


































1. Select up to five win lines your bet is split to.
2. The game is started with the "Start" button
3. If the reels stop at a winning combination, the winnings of the maximum of five betting lines will be processed according to the displayed winnings plan.



3.3) Winning combinations and the corresponding win factors









Please note that Win Factors may be limited by actual configuration!

Line wins

Winning Combination			Win Factor
			x 200
			x 100
			x 50
			x 30
			x 20
			x 18
			x 14
			x 10
			x 10
			x 10
			x 5
			x 2



Any '7' - Wins

Winning Combination		Win Factor
9 x		x 1000
8 x		x 400
7 x		x 200
6 x		x 100
5 x		x 50
4 x		x 20
3 x		x 5
2 x		x 2



'ALL' - Fruits, 'BAR' - Wins

Winning Combination		Win Factor
		x 500
		x 400
		x 300
		x 400
		x 200
		x 300
		x 100
		x 50
		x 50
		x 15



4) Caribbean Gold



Screenshot 4

4.1) Game description

Bet on up to five lines.
 Five reels spin up and stop automatically to create new winning combinations.
 The winnings for the maximum of 5 winning lines will be added.
 All wins pay left to right

4.2) Game sequence



























1. Select up to five win lines your bet is split to.
2. The game is started with the "Start" button
3. If the reels stop at a winning combination, the winnings of the maximum of five betting lines will be processed according to the displayed winnings plan.



4.3) Winning combinations and the corresponding win factors

Please note that Win Factors may be limited by actual configuration!

Line winnings

Winning Combination					Win Factor
					x 1000
					x 300
					x 50
					x 20
					x 2
					x 700
					x 200
					x 30
					x 10
					x 300
					x 75
					x 20
					x 10



Line winnings (continue 1)

Winning Combination					Win Factor
					x 200
					x 100
					x 50
					x 20
					x 500
					x 100
					x 25
					x 10
					x 200
					x 50
					x 15
					x 5



Line winnings (continue 2)

Winning Combination					Win Factor
					x 150
					x 50
					x 15
					x 10
					x 150
					x 50
					x 10
					x 5
					x 100
					x 50
					x 5
					x 3
					x 50
					x 10
					x 3
					x 2



5) Roulette



Screenshot 5

5.1) Game description

You have to guess where the ball will land.

5.2) Game sequence

Players may place their bets on the following positions:

- "Red" - "Black"
... on all red or black numbers.
- "Even" - "Odd"
... on all even or odd numbers.



- **"1-18" - "19-36"**
... on the numbers 1-18 and 19-36.
- **First dozen (1st 12)**
... on 12 consecutive numbers 1-12.
- **Second dozen (2nd 12)**
... on 12 consecutive numbers 13-24.
- **Third dozen (3rd 12)**
... on 12 consecutive numbers 25-36.
- **"Colonne"**
... on the columns 1-34, 2-35 or 3-36.
- **"Six line"**
... on six consecutive numbers consisting of two consecutive cross rows (e.g. 4-5-6-7-8-9).
- **"Corner"**
... on four numbers that create a square on the table (e.g. 1-2-4-5).
- **"Street"**
... on three consecutive numbers consisting of one cross row on the table (e.g. 1-2-3 but also 0-1-2 or 0-2-3).
- **"Split"**
... on two numbers that are either vertical or horizontal neighbours (e.g. 15/18 or 28/29).
- **"Full Number"**
... on one of the 37 numbers.
- **"Series 5 / 8"**
... on the following numbers: 5-8, 10-11, 13-16, 23-24, 27-30, 33-36.
- **"Big Series"**
... on the following numbers: 0/2/3 (2 pieces), 4-7, 12-15, 18-21, 19-22, 25-29 (2 pieces), 32-35.
- **"Orphelins Plein"**
... on the following numbers: 1, 6, 9, 14, 17, 20, 31, 34.
- **"Orphelins Cheval"**
... on the following numbers: 1, 6-9, 14-17, 17-20, 31-34.
- **"Zero Game"**
... on the following numbers: 0-3, 12-15, 26, 32-35.








5.3) Winning combinations and the corresponding win factors

<p>Full Number</p> 	<p>x 36</p>
<p>Split</p> 	<p>x 18</p>
<p>Street</p> 	<p>x 12</p>



Roulette Winning combinations (continue)

<p>Collonne (1-34 / 2-35 / 3-36)</p> 	<p>x 3</p>
<p>Dozen (1-12 / 13-24 / 25-36)</p> 	<p>x 3</p>
<p>1-18 / 19-36</p> 	<p>x 2</p>
<p>Red / Black</p> 	<p>x 2</p>
<p>Odd / Even</p> 	<p>x 2</p>



6) Royal Poker

The screenshot displays the Royal Poker game interface. At the top left, the game title "ROYAL POKER" is shown in a decorative font. To the right is a payout table for various hands:

Five Of A Kind	1100
Royal Flush	500
Straight Flush	100
Four Of A Kind	40
Full House	10
Flush	7
Straight	5
Three Of A Kind	3
Two Pairs	2
High Pair	1

To the right of the table is a "BONUS" graphic showing a hand of four Aces and a "188" value. Below the table is a "2nd Deal" banner. The main card area shows five cards: King of Hearts (held), 8 of Clubs, Joker (held), King of Clubs, and Jack of Spades. Below the cards is a control panel with buttons for "Game Selection", "Info", "Payout", "AutoHold On", "Delete Holds", "Gamble", and "Take Win". A status bar at the bottom shows "Credits: 64", "You win: 3", "Winner Paid: 1", and "Bet: 1".

Screenshot 6²

6.1) Game description

Try to win as much as possible. The game is played with 52 cards plus one Joker.

6.2) Game sequence

1. The "1st Deal" is started with the "Start" button with deduction from bets.
2. Five consecutive cards will be dealt face up. If "AutoHold" is selected, a hold suggestion will be displayed for the best possible winnings.
3. Pressing the cards will change/set a AutoHold/ManualHold suggestion.
4. The "2nd Deal" is started with the "Start" button without deduction from bets. All non-held cards will be replaced.

² The winning factor for „Five Of A Kind“ is in the version „Croatia“ 800 instead of 1.100.



6.3) Description „Aces-Bonus“

The „Aces-Bonus“ is a special win, which is given for a poker combination with 4 aces (*no joker*) additionally to the poker win.

The display value for the “Aces-Bonus” is calculated as following:

Aces Bonus = “Aces bonus win factor value” * “Actual bet value”.

The minimal bonus win factor value is 100, the maximal bonus win factor value is 500. After a Master-Reset the bonus win factor is initialized with a randomized value between 100 and 200. There is also a “hidden bonus” win factor, which is initialized with the minimal value (=100).

With every game start, the bonus win factor value is incremented by 3 percent of the minimal bet value (=1), and the “hidden bonus” win factor value is incremented by 1 percent of the minimal bet value (=1).

After giving the aces bonus win, the new aces bonus win factor value is initialized with the “hidden bonus” win factor value. The new “hidden bonus” win factor value starts again with the minimal value (=100).



6.4) Winning combinations and the corresponding win factors

<p>Five Of A Kind plus Aces Bonus</p> 	<p>$\times 1100^3$ + $\times 100 - \times 500$</p>
<p>Five Of A Kind</p> 	<p>$\times 1100$</p>
<p>Royal Flush</p> 	<p>$\times 500$</p>
<p>Straight Flush</p> 	<p>$\times 100$</p>
<p>Four Of A Kind</p> 	<p>$\times 40$</p>

³ The winning factor for „Five Of A Kind“ is in the version „Croatia“ 800 instead of 1.100.



Royal Poker - Winning combinations (continue)

<p>Full House</p> 	<p>x 10</p>
<p>Flush</p> 	<p>x 7</p>
<p>Straight</p> 	<p>x 5</p>
<p>Three Of A Kind</p> 	<p>x 3</p>
<p>Two Pairs</p> 	<p>x 2</p>
<p>High Pair</p> 	<p>x 1</p>



7) Gamble-Ladder

7.1) Description

Try to gain a higher win.

The actual win is shown by the “You win” display. The winning and losing positions - reachable from the actual win position in the Gamble-Ladder - are flashing. By pressing the “Gamble” button the gamble game is started. With the button “Take 10” the win difference (=10) between win of the actual win position (=12) and the win one position below (=2) is collected to the credit. By pressing the “Take Win” button the actual win is collected.

Info: Please note that Gamble wins may be limited by actual configuration!



Screenshot 7



Troubleshooting

Error	Cause	Help
Touch screen only works partly	<ul style="list-style-type: none"> • Cable connecting the touch screen and the PC is defect (<i>part that is connected to the PC</i>). • Missing protection earth. 	<p>⇒ Exchange the connecting cable.</p> <p>⇒ Check protection earth or ground the machine.</p>
When starting the following message appears: MEMORY TEST FAIL	<ul style="list-style-type: none"> • PC Memory defect. 	<p>⇒ Exchange the PC.</p>
White screen	<ul style="list-style-type: none"> • Graphic card defect. 	<p>⇒ Exchange the PC.</p>
Touch screen does not work after exchanging the PC	<ul style="list-style-type: none"> • Possibly not calibrated. 	<p>⇒ Calibrate the touch screen (press red button on the machine, go to operator mode).</p>
Touch screen cannot be calibrated properly	<ul style="list-style-type: none"> • Missing data in touch controller buffer. 	<p>⇒ Switch to operator mode; turn off the machine; keep red button on machine pressed (controller buffer is deleted); then press operator button again; start machine anew.</p>
Touch screen does not work and/or LED on the rear side of the PC is flashing	<ul style="list-style-type: none"> • Touch screen controller or touch screen cable is defect. 	<p>⇒ Check cable between touch screen and controller, exchange defect controller or exchange PC.</p>
No function	<ul style="list-style-type: none"> • The main plug is not plugged in. • The main switch is not on. • Fuse is burnt. 	<p>⇒ Plug in main plug.</p> <p>⇒ Switch on main switch.</p> <p>⇒ Install new fuse.</p>
No picture	<ul style="list-style-type: none"> • Net cable not connected to monitor. • Video connection not plugged in. • Monitor defect. 	<p>⇒ Check power supply of monitor and connections.</p> <p>⇒ Plug in video connections.</p> <p>⇒ Exchange monitor.</p>
No sound	<ul style="list-style-type: none"> • Volume controller is not turned on. • Audio cable is not connected • Loudspeaker defect. 	<p>⇒ Turn up volume.</p> <p>⇒ Plug in audio cable.</p> <p>⇒ Exchange loudspeaker.</p>




One or more pushbuttons do not work.	<ul style="list-style-type: none"> • Plug is not plugged in • Pushbutton is not installed properly or defect. 	<p>⇒ Check plug connections.</p> <p>⇒ Check or exchange Pushbuttons.</p>
Coins are counted wrongly	<ul style="list-style-type: none"> • Wrong value programmed 	<p>⇒ Check program setup</p>
Inserted coins fall through	<ul style="list-style-type: none"> • No power at coin acceptor • Dirty coin acceptor • Coin channel not programmed • Coin acceptor defect 	<p>⇒ Check power supply</p> <p>⇒ Clean coin acceptor</p> <p>⇒ Change programming</p> <p>⇒ Exchange coin acceptor</p>
Low coin acceptance	<ul style="list-style-type: none"> • Coin acceptor is dirty 	<p>⇒ Clean coin acceptor</p>
Low bill acceptance	<ul style="list-style-type: none"> • Bill reader is de-calibrated 	<p>⇒ Calibrate bill-reader</p>
Counter does not work	<ul style="list-style-type: none"> • Counter defect 	<p>⇒ Check connection; exchange counter</p>
Error message on the screen “Program Error (hard disc)”, no more credits will be accepted; no more action is possible from the player; operator invention is required!	<ul style="list-style-type: none"> • Integrity check at startup failed. 	<p>⇒ An update has to be performed with an update disk with the same version by an authorized person.</p> <p>After that the Critical Memory will be restored from the data's in the FRAM (if they are correct) to the hard disk.</p> <p>If the error remains, the hard disk is defect and must be changed (see below).</p>
In this case, mostly the machine will not work anyway.	<ul style="list-style-type: none"> • Hardware error of HDD 	<p>⇒ Hard disk have to be changed by an authorized person only with a hard disk containing the same version or with a new hard disk but then an update has to be performed on the machine with an update disk containing the same version.</p> <p>After that the Critical Memory will be restored from the data's in the FRAM (if they are correct) to the hard disk.</p>



<p>A "blue screen" will be shown and the machine stops immediately.</p>	<p>Hardware error of FRAM</p>	<p>⇒ I/O Controller card have to be changed by an authorized person only.</p> <p>After that the "Critical Memory" will be restored from the data's on the hard disk (if they are correct) to the FRAM on the new I/O Controller card.</p>
---	-------------------------------	---



Cable Plan



Declaration of CE conformity



Declaration of CE conformity

Document-no.: QZ/1000/056/01/280306

Producer: TAB AUSTRIA
Industrie- und Unterhaltungselektronik GmbH & Co KG

Address: Haiderstraße 40
A-4052 Ansfelden
Tel.no.: 07229/78040, Fax-no.: 07229/78660

Description of good: Betting terminal
Type: NEVADA

This mentioned product corresponds to the following European Regulations:

Criterion: 73/23/EWG
Criterion of the council for the adaptation of the legal regulations of the member states, concerning electrical working founds for using within limited tension bounds, changed by RL 93/68/EWG.

Criterion: 89/336/EWG
Criterion of the council for the adaptation of the legal regulations of the member states, concerning the electromagnetic compatibility changed by RL 91/263/EWG, 92/31/EWG, 93/68/EWG and 93/97/EWG.

The conformity of the mentioned product with the regulations of the criterions is shown through the observance of the relevant sections of the following norms:

Matched European norms:	Document	Issuing date
	EN 55022	1998
	EN 55024	1998
	EN 60950	2000
	EN 61000-3-2	2000
	EN 61000-3-3	2000

Issued by: GF

Managing Director: Ing. Siegfried Dattl jun.

Place, date: Ansfelden, March 28th 2006

Legally binding signature: 



Industrie- und Unterhaltungs-
elektronik GmbH & CoKG
A-4052 Ansfelden
Haider Straße 40
Tel. +43 (0)7229/78040-0
Fax +43 (0)7229/ 78660
www.tab.at, sales@tab.at

The declaration certifies the conformity with the mentioned criterions, but it doesn't include the assurance of characteristics. The safety regulations of the delivered goods have to be read through carefully.



END-USER LICENSE AGREEMENT FOR MICROSOFT SOFTWARE

IMPORTANT - READ CAREFULLY: This End-User License Agreement ("EULA") is a legal agreement between you (either an individual or a single entity) and the manufacturer ("Manufacturer") or the special purpose computing device ("SYSTEM") you acquired which includes certain Microsoft software product(s) installed on the SYSTEM ("SOFTWARE PRODUCT" or "SOFTWARE"). The SOFTWARE includes computer software, the associated media, any printed materials, and any "online" or electronic documentation. By installing, copying or otherwise using the SOFTWARE, you agree to be bound by the terms of this EULA. If you do not agree to the terms of this EULA, Manufacturer and Microsoft Corporation ("Microsoft") are unwilling to license the SOFTWARE to you. In such event, you may not use or copy the SOFTWARE, and you should promptly contact Manufacturer for instructions on return of the unused product(s) for a refund.

SOFTWARE LICENSE

The SOFTWARE is protected by copyright laws and international copyright treaties, as well as other intellectual property laws and treaties. The SOFTWARE is licensed, not sold.

1. GRANT OF LICENSE. This EULA grants you the following rights:

- **Software.** You may use the SOFTWARE as installed on the System.
- **Application Sharing.** The SOFTWARE may contain technology that enables applications to be shared between two or more SYSTEMS, even if an application is installed on only one of the SYSTEMS. You should consult your application license agreement or contact the application licensor to determine whether sharing the application is permitted by its licensor.
- **Storage/Network Use.** If the SOFTWARE PRODUCT is installed on the SYSTEM over an internal network from a server, you must acquire and dedicate a license for the SOFTWARE PRODUCT for each SYSTEM on which the SOFTWARE PRODUCT is used or to which it is distributed. A license for the SOFTWARE PRODUCT may not be shared or used concurrently on different SYSTEMS.
- **Back-up Copy.** If MANUFACTURER has not included a copy of the SOFTWARE on separate media with the SYSTEM, you may make a single copy of the SOFTWARE for use solely for archival purposes with the SYSTEM.

2. DESCRIPTION OF OTHER RIGHTS AND LIMITATIONS.

- **Limitation on Reverse Engineering, De-compilation and Disassembly.** You may not reverse engineer, decompile, or disassemble the SOFTWARE, except and only to the extent that such activity is expressly permitted by applicable law notwithstanding this limitation.



- **Single SYSTEM.** The SOFTWARE is licensed with the SYSTEM as a single integrated product. The SOFTWARE may only be used with the SYSTEM.
- **Rental.** You may not rent or lease the SOFTWARE.
- **Software Transfer.** You may permanently transfer all of your rights under this EULA only as part of a sale or transfer of the SYSTEM, provided you retain no copies, you transfer all of the SOFTWARE (including all component parts, the media, any upgrades or backup copies, and this EULA, and if applicable, the Certificate(s) of Authenticity), and the recipient agrees to the terms of this EULA. If the SOFTWARE is an upgrade, any transfer must include all prior versions of the SOFTWARE.
- **Termination.** Without prejudice to any other rights, Manufacturer or Microsoft may terminate this EULA if you fail to comply with the terms and conditions of this EULA. In such event, you must destroy all copies of the SOFTWARE and all of its component parts.
- **Single EULA.** The package for the SOFTWARE may contain multiple versions of this EULA, such as multiple translations and/or multiple media versions (e.g., in the user documentation and in the software). In this case, you are only licensed to use one (1) copy of the SOFTWARE PRODUCT.

3. UPGRADES AND RECOVERY MEDIA.

- If the SOFTWARE is provided by Manufacturer on media separate from the SYSTEM and is labeled "For Upgrade Purposes Only" (Upgrade SOFTWARE), you may install one copy of the Upgrade SOFTWARE onto the SYSTEM as a replacement copy for the SOFTWARE originally installed on the SYSTEM and use it in accordance with Section 1 of this EULA. You may also install additional copies of the Upgrade SOFTWARE as replacement copies onto additional SYSTEMS which are the same brand and model as the SYSTEM and contain a duly licensed copy of the same version and language release of the SOFTWARE ("ADDITIONAL SYSTEMS"), provided that (1) Manufacturer has supplied a corresponding serialized sticker for each additional copy of the Upgrade SOFTWARE, and (2) you affix a serialized sticker per Manufacturer's instructions for each unit of Upgrade SOFTWARE you install.
- If the SOFTWARE is provided by Manufacturer on separate media and labeled as "Recovery Media", you may not make a copy of the SOFTWARE as described in Section 1 for archival purposes. Instead, you may use the Recovery Media solely to restore or reinstall the same version and language release of the SOFTWARE as originally installed on the SYSTEM and thereafter use the SOFTWARE as restored or reinstalled in accordance with Section 1 of this EULA. A single unit of Recovery Media may be used by you to restore or reinstall the SOFTWARE on ADDITIONAL SYSTEMS.

4. COPYRIGHT.

- All title and copyrights in and to the SOFTWARE (including but not limited to any images, photographs, animations, video, audio, music, text and "applets," incorporated into the SOFTWARE), the accompanying printed materials, and any copies of the SOFTWARE, are owned by Microsoft or its suppliers. You may not copy the printed materials accompanying the SOFTWARE. All rights not specifically granted under this EULA are reserved by Microsoft.



5. PRODUCT SUPPORT.

- Product support for the SOFTWARE is not provided by Microsoft or its subsidiaries. For product support, please refer to Manufacturer's support number provided in the documentation for the SYSTEM. Should you have any questions concerning this EULA, or if you desire to contact Manufacturer for any other reason, please refer to the address provided in the documentation for the SYSTEM.

6. LIMITED WARRANTY.

- **Limited Warranty.** Manufacturer warrants that the SOFTWARE will perform substantially in accordance with the accompanying written materials for a period of ninety (90) days from the date of receipt. Any implied warranties on the SOFTWARE are limited to ninety (90) days. Some states/jurisdictions do not allow limitations on duration of an implied warranty, so the above limitation may not apply to you.
- **Customer Remedies.** Manufacturer's and its suppliers' entire liability and your exclusive remedy shall be, at Manufacturer's option, either (a) return of the price paid, or (b) repair or replacement of the SOFTWARE that does not meet the above Limited Warranty and which is returned to Manufacturer with a copy of your receipt. This Limited Warranty is void if failure of the SOFTWARE has resulted from accident, abuse, or misapplication. Any replacement SOFTWARE will be warranted for the remainder of the original warranty period or thirty (30) days, whichever is longer.
- **No Other Warranties.** EXCEPT AS EXPRESSLY PROVIDED IN THE LIMITED WARRANTY SECTION ABOVE, THE SOFTWARE IS PROVIDED TO THE END USER "AS IS" WITHOUT OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND/OR FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK OF THE QUALITY AND PERFORMANCE OF THE SOFTWARE IS WITH YOU.
- **No Liability for Consequential Damages.** MANUFACTURER'S SUPPLIERS SHALL NOT BE HELD TO ANY LIABILITY FOR ANY DAMAGES SUFFERED OR INCURRED BY THE END USER (INCLUDING, BUT NOT LIMITED TO, GENERAL, SPECIAL, CONSEQUENTIAL OR INCIDENTAL DAMAGES INCLUDING DAMAGES FOR LOSS OF BUSINESS PROFITS INTERRUPTION, LOSS OF BUSINESS INFORMATION AND THE LIKE), ARISING FROM OR IN CONNECTION WITH THE DELIVERY, USE OR PERFORMANCE OF THE SOFTWARE.

1. NOTE ON JAVA SUPPORT.

- THE SOFTWARE PRODUCT MAY CONTAIN SUPPORT FOR PROGRAMS WRITTEN IN JAVA. JAVA TECHNOLOGY IS NOT FAULT TOLERANT AND IS NOT DESIGNED, MANUFACTURED, OR INTENDED FOR USE OR RESALE AS ON-LINE CONTROL EQUIPMENT IN HAZARDOUS ENVIRONMENTS REQUIRING FAIL-SAFE PERFORMANCE, SUCH AS IN THE OPERATION OF NUCLEAR FACILITIES, AIRCRAFT NAVIGATION OR COMMUNICATION SYSTEMS, AIR TRAFFIC CONTROL, DIRECT LIFE SUPPORT MACHINES, OR WEAPONS SYSTEMS, IN WHICH THE FAILURE OF JAVA TECHNOLOGY COULD LEAD DIRECTLY TO DEATH, PERSONAL INJURY, OR SEVERE PHYSICAL OR ENVIRONMENTAL DAMAGE.



Warranty terms by TAB-AUSTRIA Industrie und Unterhaltungselektronik Gesellschaft m.b.H. & Co KG

(Tab hereinafter)

We are granting a warranty for this machine under the following conditions:

Insofar as the “General Terms of Business of TAB-AUSTRIA Industrie- und Unterhaltungselektronik GmbH & Co KG” are not modified by the following, which sets out the conditions and scope of our warranty performance, these terms will continue to apply without change.

The warranty period for our products from delivery is:

- 24 months for all Silverball Terminals (Silverball Strato, Silverball Strato Max, Silverball Cosmo, Silverball Cosmo Max, Silverball Pro, Silverball Max Pro, Silverball Beetle Pro, Silverball Beetle Max Pro)
- 24 months for Max Fire, Max Fire Video, Virtual Pinball, Golden Island
- 12 months for all other products, particularly betting terminals
- Six months for all spare parts; however, if a warranty period of more than six months still obtains for the machines, this period will apply in its entirety to the spare part.

The warranty will only be granted for new products by TAB, not for their spare parts, not for products of different brands and manufacturers and corresponding spare parts. No warranty is granted for used products either.

In accordance with the following provisions, we shall repair defects to the machine that have been demonstrably caused by a material and/or manufacturing fault which already existed at the time the product was handed over, and which was reported within 14 days of it becoming apparent to our sales partner or the first end user while still within the warranty period. No warranty is assumed for used machines.

The warranty exclusively covers such components that are essential to operating the product. It does not include easily damaged parts or wearing parts, such as, for example, glass, plastic or light bulbs. Minor deviations from the desired composition insignificant to the value and usability of the machine will not result in any warranty obligations. Damage caused by physical, chemical, electrical or electrochemical or other effects not related to the customary dedicated use will not result in any warranty obligations; neither does damage caused by water or abnormal environmental conditions or inappropriate operating conditions. Also, no warranty can be assumed for machine defects caused by transport damage for which we are not responsible, incorrect installation and assembly, incorrect use, non-observance of operating or assembly instructions or lack of care.

The warranty claim becomes void if repairs or interventions have been carried out by the customer himself/herself or by persons who were not accordingly authorized or who were not



authorized by us or in the event of our machines being fitted with spare, supplementary or accessory parts that are not original parts, or if parts have been removed.

The warranty performance will be made in such a way that defective components will at our discretion be repaired or replaced with faultless components free of charge unless improvement or exchange are impossible or would result in for us unreasonable cost. In such cases, a reduction in price or, in the event of not only a minor defect, cancellation of sale may be claimed.

Machines for which a warranty performance is being claimed on the basis of this warranty must be handed over or sent to us. Repairs at the installation site are not possible. The customer will bear transport costs and the transport risk.

Exchanged parts will become our property.

Warranty performances will neither result in an extension of the warranty period nor will they initiate a new warranty period.

Further or other claims (in particular claims for damages suffered beyond the machine) are excluded insofar as liability is not mandatory by law.

These warranty terms apply to machines purchased and operated in Austria. They apply to machines conveyed to other countries only insofar as they possess the technical requirements (e.g. voltage, frequency, etc.) for the corresponding country, have been officially approved for use there and are suited to the individual climate and environmental conditions.

The TFT LCD display consists of more than 1,000,000 Thin-Film Transistors (TFT). A small amount of missing, black, or luminous points is characteristic for TFT LCD technology. The warranty performance will be granted if more than 15 missing, black, or luminous points are present.

Version dated January 8, 2008



In case of any irregularities in the machine, please check power and all plug-in connections!

In case you cannot remove an error, please call our hotline:

Call +43-7229-780 40 – ext. 250



Notes

