

Technical Information

➔ Better games through innovation!

www.tab.at

Technical information WLAN network with Access Point

TAB-Austria Industrie- und Unterhaltungselektronik GmbH & CoKG

Haider Strasse 40, A-4052 Ansfelden

Tel.+43 (0)7229/78 040-0*, Fax +43 (0)7229/78 660, e-mail: sales@tab.at

Hotline: +43 (0)7229/78 040-250, e-mail: hotline@tab.at





This **technical information** is used for the setup and configuration of a WLAN network with Access Point.

At the picture below you can see how to use WLAN and LAN in one network with a DSL connection. This means, that you can use a dual-network!

The complete and detailed configuration can be found at Page 3 of this technical information.

This works for all Silverball machines, Max Fire / Video and Virtual Pinball terminals!





Configuration of the WLAN network

- 1) Connect your machine with a network cable to the WLAN module.
- 2) Start the machine
- 3) After starting switch to Testmode „ON“
- 4) Select „Championsnet“ and choose the Option „Change“ at the Connection type

Machine/Set-up site

Machine number	31527	
Name of the establishment	LuckyStrato12	
Place/Town	4052	
Address	Address	
Telephone number	Telefon	
Fax number	Fax	
Email	Email	
Country	Germany	<input type="button" value="change"/>

Connection (Network - Direct)

Telephone number		
User name		<input type="button" value="change"/>
Time	18:30	

<input type="button" value="Test connection"/>	<input type="button" value="Protocol"/>	<input type="button" value="ChampionsNet"/>
<input type="button" value="Register ..."/>	<input type="button" value="Email"/>	<input checked="" type="checkbox"/> activate
<input type="button" value="Receive datas"/>	<input type="button" value="WWW"/>	<input type="button" value="Help"/>
	<input type="button" value="Info Terminal"/>	<input type="button" value="Back"/>

- 5) Now choose „Network Direct“

Provider connection

Telephone number	<input type="text"/>	<input type="button" value="change"/>
User name	<input type="text"/>	<input type="button" value="change"/>
Password	<input type="text"/>	<input type="button" value="change"/>
Confirmation	<input type="text"/>	<input type="button" value="change"/>

Start of transmission

<input checked="" type="radio"/> Hour	<input type="radio"/> Minute	<input type="button" value="+"/>
18	30	<input type="button" value="--"/>

Connection Type

- Modem
- External Modem
- Network - Direct
- Network - VPN
- Network - PPPOE

Permanent Connection





- 6) After that please choose now „Page 2“ to set-up the network settings. On the recommended module with the options “Client Mode” and “DHCP” you can activate here the options “Disable DNS” and “Use DHCP”

Proxy / Auto Configuration Script

Enable Proxy ändern

Enable Config Script ändern

DNS

Disable DNS

Domain: ändern

DNS1: ändern

DNS2: ändern

Show MAC Address

Network Info

Use DHCP

IP Address: ändern

Subnet Mask: ändern

Gateway: ändern

Silverball Max Terminal

Enable Max Terminal

SB-Max IP: ändern

Übernehmen

Zurück

- 7) The configuration of the WLAN Access Point modules have to be made with a Home PC and the Internet Explorer! Please read the technical information for your WLAN Access Point module carefully.

Note:

Please note, that we recommend a WLAN Access point module where the options „DHCP“ and „Client Mode“ are available and activated!





Notes

